

Arcade Collection System Setup Menus

CONTENTS

Contents	1
System Setup Menus	3
Getting Started	3
Main Menu	3
General Settings	4
Adjust Screen.	4
Button Check	5
Game Mode	5
Volume (Sound)	6
Factory Reset.	6
Silver Strike Bowling Main Menu	7
General Settings	7
Operator Adjustables	8
General Adjustments	8
Sound Adjustments	9
Reset to Factory Settings	9
System Tests	10
Video Tests	10
Color Adjustments	11
Contrast Adjustments	11
Screen Size Adjustment	11
Sound Tests	12
Player Control Tests	12
Mechanical Meter Test	12
Hardware Tests	13
Hardware/Software	13
System Info	13
USB Info	13
Version Info	13
Check Hard Drive	14
Check Cooling	14
Troubleshooting Shortcuts	15
Silver Strike Settings	15
Game Options	16
Reset Leaderboards	17
PowerPutt Golf Main Menu	18
General Settings	18
Operator Adjustables	19
General Adjustments	19
Sound Adjustments	20
Reset to Factory Settings	21
System Tests	21
Video Tests	21
Color Adjustments	22
Contrast Adjustments	22

Arcade Collection®

© Copyright Incredible Technologies, Inc. All Rights Reserved. Unauthorized duplication is a violation of applicable law. All other marks are the properties of their respective owners. All rights reserved. Commercial.

Screen Size Adjustment	. 22
Sound Tests	. 23
Player Control Tests	. 23
Hardware Tests	. 24
Hardware/Software	. 24
Check Hard Drive	. 25
Check Cooling	. 25
Troubleshooting Shortcuts	. 26
Game Options	. 26
Reset Leaderboards	. 27
Target Toss Pro Main Menu	. 28
General Settings	. 28
Operator Adjustables	. 29
General Adjustments	. 29
Sound Adjustments	. 30
Reset to Factory Settings	. 30
System Tests	. 31
Video Tests	. 31
Color Adjustments	. 32
Contrast Adjustments	. 32
Screen Size Adjustment	. 32
Sound Tests	. 33
Player Control Tests	. 33
Mechanical Meter Test	. 33
Hardware Tests	. 34
Hardware/Software	. 34
Check Hard Drive	. 35
Check Cooling	. 35
Troubleshooting Shortcuts	. 36
Game Options	. 36

GETTING STARTED

Navigating the Menu System

The System Setup menus cover a variety of important areas including collections, tests, game adjustments, and optional settings. You should familiarize yourself with these menus, as they are designed to optimize your game for your location and your business. Pay particular attention to the Collection menus, as they will detail how much money to give to your location. There are also menus that allow you to adjust various split percentages for a variety of different charges. These screens can help you maximize your investment and involve your location in the costs associated with your equipment.

Entering System Setup Mode

There are two ways to enter System Setup. Open the coin door and press the Test button to access the game's System Setup software menu system. Or, from the I/O Board, move the DIP switch SW202 position 4 to the ON position. This switch needs to be moved back to OFF to exit the System Setup menus. Refer to the diagram in Appendix D for all DIP switch settings.

Selecting a Menu

A menu option can be selected at any time by rolling the trackball up or down or by pressing the Left or Right buttons.

Choosing a Menu/Option

A menu option can be chosen at any time by pressing the Start button.

Changing a Value

A value can be changed at any time by rolling the trackball left or right.

Note: Some features may not be allowed in certain state or local jurisdictions. Be sure to check your local laws before activating or allowing any features that may be questionable in your area.

MAIN MENU

The Main Menu displays five main areas that make up System Setup mode. Please familiarize yourself with these areas, as they will help you maximize your earnings potential.

General Settings

Adjust operator settings, perform system tests, and reset your game back to factory settings.

Silver Strike Bowling

Settings for Silver Strike Bowling, such as Collections and Earnings and Silver Strike Settings

PowerPutt Golf

Settings for PowerPutt Golf, such as Collections and Earnings and PowerPutt Golf Settings

Target Toss Pro

Settings for Target Toss Pro, such as Collections and Earnings and Target Toss Pro Settings

Collections & Earnings

Not available in Arcade Collection Home Edition

Exit

This will exit the System Setup menus and return to the game's attract mode.



Arcade Collection®

GENERAL SETTINGS

The General Settings menu houses various adjustable settings relating to the cabinet and is divided into two sections.

Adjust Screen

Align your monitor so that all the circles appear as circles and the boundary line appears on the edge of each side of the screen.

Button Check

Test all inputs including trackball, buttons, and money slots.

Game Mode

Toggle between Money/Free Play. The default is set to Money Play.

Volume

Adjust the various sound settings including attract mode sounds, game volume, and stereo setup.

Factory Reset

Reset all the settings found in the General section to factory defaults.

Exit

This will take you back to the Main Menu

ADJUST SCREEN

Use this screen to adjust the size and aspect ratio of your picture. Press the Start button to exit.

If you are using an HDTV display, you may need to adjust this screen to see the complete image. Use the trackball to highlight LARGER or SMALLER and press the Start button to adjust the screen image. Press EXIT to return to Main Menu.

Note: Adjusting the screen size will prompt a reboot upon exiting this menu.





BUTTON CHECK

Use this screen to test all of the inputs, including the trackball, buttons, money slots and card reader. When an input is active the appropriate graphic image will light. Press the Left, Right and Start buttons simultaneously to exit this test screen.

When testing the trackball, the Current value will change depending on the direction the ball is spinning. The Max value will display the largest number reached during the test. There is no exact number to determine whether a trackball is malfunctioning, but in general the Max number should be close to the same when spinning up and down, and close to the same when spinning left and right.

When testing coin and bill acceptor switches, the number of pulses will appear below the appropriate image.

On the keypad the numbers illuminate when pressed.

GAME MODE

Game Mode

Choose Between MONEY PLAY or FREE PLAY.

Reset Values

This option allows you to reset the settings found in the General Adjustments menu to their factory defaults.

Exit

This will take you back to the Main Menu.

PRESS BLUE + YELLOW + RED TO EXIT FX: 0 NT: O MRX: O K: 0 NT: O **T:** 0 T: 0 COIN 1 COIN 2 SERV. TEST \$ Œ Œ VOL. + VOL O PULSES O PULS



VOLUME (SOUND)

Game Volume

This option lets you adjust the In Game volume from OFF to 100%. The default is set to 30%.

Attract Volume

This option lets you adjust the Attract Mode volume from OFF to 100%. The default is set to 30%.

Attract Mode Sound

This adjusts how often sounds are played in Attract Mode: Never, Rarely, Sometimes, Often and Always. **The default is set to On – Sometimes.**

Reset Values

This resets all values to their default value located on this page.

Exit

This will take you back to the Main Menu.

FACTORY RESET

This menu will reset ALL settings in the General section to their default values. A verification screen will display to make sure you agree to the change.

Note: This process may take several minutes to complete.





SILVER STRIKE BOWLING MAIN MENU

The Main Menu displays five main areas that make up System Setup mode. Please familiarize yourself with these areas, as they will help you maximize your earnings potential.

Collections & Earnings – N/A on Arcade Collection Home Edition

General Settings

This area allows you to change operator adjustables, perform system tests, and reset your game back to factory settings.

Troubleshooting Shortcuts

This section presents a variety of tests and

menus that will help you troubleshoot any problems you may be having with your game. The available sections are also accessible through the other main sections.

₩

Operator Adjustables page

to Move

Silver Strike Settings

This area allows you to adjust settings specific to Silver Strike LIVE including the player cost schedule, game features, and game audits.

Note: Always **Exit** out to the attract mode when making changes to menu configurations or settings to save changes. If the cabinet is shut down while operator adjustable settings menus are still open, the changes will not be saved.

Exit

This will exit the System Setup menus and take you back into the game's attract mode.

GENERAL SETTINGS

The General Settings menu houses various adjustable settings relating to the cabinet and is divided into three sections.

Operator Adjustables

This area allows you to adjust options like volume, attract mode sounds, and money slot settings.

System Tests

This area allows you to perform diagnostics including video adjustments, input tests, and sound tests.

Advertisements

This area allows you to manage various graphic and text advertisements on your machine. This section is currently unavailable but is planned for a future update.

Back

This will take you back to the Main Menu.



Main Menu

Collections & Earnings

General Settings

Troubleshooting Shortcuts

Silver Strike Settings

Exit

Press Start to Choose

This will exit you back into the main Arcade Collection

🖛 🔿 to Change

Arcade Collection®

ection[®] Version 1/10/23 © Copyright Incredible Technologies, Inc. All Rights Reserved. Unauthorized duplication is a violation of applicable law. All other marks are the properties of their respective owners. All rights reserved. Commercial.

OPERATOR ADJUSTABLES

This menu contains adjustable settings that pertain to you and your business. Please familiarize yourself with this section to help you maximize the game's earning potential.

General Adjustments

This area allows you to adjust options like coin message, game mode and monitor mode.

Money Slot Adjustments

This area allows you to adjust the settings of your various money slots on your cabinet.

Sound Adjustments

This area allows you to adjust the various sound settings including attract mode sounds, game volume, and stereo setup.

Collection Settings

This important area allows you to adjust splits and view various fees for your collections.

Reset To Factory Settings

This option allows you to reset all the settings found in the Operator Adjustables section to factory defaults.

Back

This will take you back to the General Settings menu.

GENERAL ADJUSTMENTS

Coin Message

Is set to "Insert \$" by default and requires the player to insert money. No other modes are available.

Game Mode

This lets you toggle between money/free play. The default is set to Money Play.

2nd Monitor Mode

You can connect a second monitor to the extra video connector on the system box, which is great for promotions or special events. Ensure the Current Value is set VGA.

Reset Values

This resets all values to their default value located on this page.

Back

This will take you back to the **Operator Adjustables** menu.

to Move to Move	← → to Change	Press Start to Choose
	Current Value	Default Value
Coin Message:	"Insert S"	"Insert \$"
Game Mode:	Money Play	Money Play
2nd Monitor Mod	e S-Video	S-Video



SOUND ADJUSTMENTS

In Game Volume

This option lets you adjust the In Game volume from OFF to 100%. When routing audio through the television, the Game Volume Setting needs to be adjusted up to 75%. Then use the television volume control as the Master Volume. **The default is set to 30%.**

Attract Volume

This option lets you adjust the Attract Volume from OFF to 100%. The default is set to 20%.

Attract Mode Sounds

This adjusts how often sounds are played in the attract mode: Never, Rarely (every 20th time), Sometimes (every 10th time), Often (every 5th time), and Always. **The default is set to On - Sometimes.**

Stereo/Mono

This option is where you select stereo or mono setup. The default is set to Stereo.

Reset Values

This resets all values to their default value located on this page.

Back

This will take you back to the **Operator Adjustables** menu.

RESET TO FACTORY SETTINGS

This menu will reset ALL settings in the Operator Adjustments section to their default values. A verification screen will display to make sure you agree to the change.





SYSTEM TESTS

This area allows you to perform diagnostics including video adjustments, input tests, and sound tests.

Video Tests

This area has tests that will help you to adjust your game's color, contrast, and screen size.

Sound Tests

This area has tests that will help you adjust your game's audio setup by playing a stored sound, a streaming sound, and testing the speaker(s).

Player Control Tests

This option allows you to test all inputs including trackball, buttons, money slots and card reader.

Mechanical Meter Test

This test makes the hard meter adjust by one to make sure it is functioning properly.

Hardware Tests

This area includes a series of diagnostic screens and tests to help you make sure your game is functioning correctly.

Back

This will take you back to the General Settings menu.

VIDEO TESTS

The Video Tests section has a variety of tests that will help you adjust your monitor.

Color Adjustments

This area will take you to a series of tests to adjust your monitor's RGB settings to have each color display properly.

Contrast Adjustments

This area will take you to a series of tests to adjust your monitor's brightness/contrast so the game displays properly.

Screen Size Adjustment

Use this screen to align your monitor so that all the circles appear as circles and the boundary line appears on the edge of each side of the screen.

Back

This will take you back to the **System Tests** menu.

Player Control Tests
Mechanical Meter
Hardware Tests
(> Back
(USA) Silver Strike Bowling 2.00.01 T-Game ID 19-137504
help you make sure your game is functioning
ou adjust your monitor.
Video Tests

System Tests

Press Start to Choose

This selection will take you back to the previous menu.

🖛 <table-cell-rows> to Change

Video Tests

Sound Tests

to Move

Video Tests
This will take you back to the System Tests menu.
↑↓ to Move ← → to Change Press Start to Choose
Color Adjustments
Contrast Adjustments
Screen Size Adjustments
(> Back
(USA) Silver Strike Bowling I.00.03 T-Game ID 19-000005

COLOR ADJUSTMENTS

Color Grid Adjustment

Adjust your monitor to have each colored box display properly.

Red Screen

Adjust your monitor to have red display properly.

Green Screen

Adjust your monitor to have green display properly.

Blue Screen

Adjust your monitor to have blue display properly.

Back

This will take you back to the Video Tests menu.

CONTRAST ADJUSTMENTS

White Screen

Adjust your monitor to have white display properly.

50% White Screen

Adjust your monitor to have 50% white display properly.

25% White Screen

Adjust your monitor to have 25% white display properly.

Black Screen

Adjust your monitor to have black display properly.

Contrast Screen

This option is a test you can use to adjust your monitor's contrast and brightness settings to have the boxes displayed properly.

Note: May not work on older or often used monitors. If you have a monitor that's old or has been used often you may not be able to adjust the contrast and/or brightness levels accordingly. In this case adjust the monitor for best performance while getting close to the recommended settings.

Back

This will take you back to the Video Tests menu.

SCREEN SIZE ADJUSTMENT

Use this screen to adjust the size and aspect ratio of your picture. Press the Start button to exit.

If you are using an HDTV display, you may need to adjust this screen to see the complete image. Use the trackball to highlight **Bigger** or **Smaller** and press the Start button to adjust the screen image. (Only available in 1280x720 resolutions.) Press **Done** to exit.

Note: Adjusting the screen size will prompt a reboot upon exit of this menu.







Arcade Collection®

ection[®] Version 1/10/23 © Copyright Incredible Technologies, Inc. All Rights Reserved. Unauthorized duplication is a violation of applicable law. All other marks are the properties of their respective owners. All rights reserved. Commercial.

SOUND TESTS

Stored Sound

This will play a stored sound so you can make sure your audio setup is functioning properly.

Streaming Sound

This will play a streaming sound so you can make sure your audio setup is functioning properly.

Speaker Test

This test will say MONO if you have your game set to Mono or LEFT and RIGHT if you have it set to stereo so you can make sure your audio setup is functioning properly.

Back

This will take you back to the **System Tests** menu.

PLAYER CONTROL TESTS

Use this screen to test all of the inputs, including the trackball, buttons, money slots and card reader. When an input is active the appropriate graphic image will light. Press the Left, Right and Start buttons simultaneously to exit this test screen.

Sound_Tests	
This will take you back to the System Tests menu.	
↑↓ to Move ← → to Change Press Start to Change	oose
Stored Sound	
Streaming Sound	
Speaker Test	
Back	
(USA) Silver Strike Bowling I.00.03 T-Game ID 19-00000	5



MECHANICAL METER TEST

Click Meter

This test makes the hard meter adjust by one to make sure it is functioning properly.

Back

This will take you back to the System Tests menu.

Mechanical Meter Test
This will take you back to the System Tests menu.
↑↓ to Move
Click Meter
• Back
(USA) Silver Strike Bowling I.OO.O3 T-Game ID 19-000005

HARDWARE TESTS

This area includes a series of diagnostic screens and tests to help you make sure your game is functioning correctly.

Hardware/Software

This area has options to view your system and USB info.

Check Hard Drive

This test checks the integrity of your hard drive's data. *Note: This test can take several minutes.*

Check Cooling

This test helps you make sure your game is functioning at the proper temperature and all fans are working.

Check Card Reader

This test will test the functionality of the card reader, and display some details on the card that is tested.

Back

This will take you back to the System Tests menu.

HARDWARE/SOFTWARE

System Info

This is a list of your game's current basic system info.

USB Info

This is a list of your game's current USB devices.

Version Info

This is a list of your game's software version.

Back

This will take you back to the Hardware Tests menu.

SYSTEM INFO

This is a list of your game's current basic system information, including Hard Drive, CPU and Video Card.

USB INFO

This is a list of your game's current USB devices.

VERSION INFO

This is a list of your machine's software version.







Version 1/10/23
© Copyright Incredible Technologies, Inc. All Rights Reserved. Unauthorized duplication is a violation of applicable law. All other marks are the properties of their respective owners. All rights reserved. Commercial.

CHECK HARD DRIVE

Check File Data

This test checks the integrity of your hard drive's data.

Select Begin Test to initiate the process.

Note: This test can take up to 3 hours to complete.

If this test succeeds you will see the message: **Status: Hard Drive Functioning Properly.** If this test fails, you will see the message: **Hard Drive Error (#)**

Select **Back** to skip the test and return to the **Hardware Tests** menu.

Check File System

This test REBOOTS YOUR GAME and performs a low level systems check of the integrity of your hard drive.

Note: This can take several minutes.

Back

This will take you back to the Hardware Tests menu.

CHECK COOLING

This checks that your game is functioning at the proper temperature and all fans are working. The current status is color-coded for easy viewing. If the results are displayed in green, your cabinet is at normal settings.

Note: Cooling information on your system may show up as dashed lines just as shown in the picture. This is because some motherboards do not allow external access to the temperature and fan speeds. This should not be considered a problem.

Back

The Back button takes you back to the **Hardware Tests** menu.



Check Cooling		
This checks that your game is functioning at the proper temperature and all fans are working. The Back button takes you back to the previous menu.		
↑↓ to Move ← → to Change	Press Start to Choose	
Processor Fan (RPM)		
Cabinet Fan (RPM)		
Case Fan (RPM)		
Processor Temp (Celsius)		
Internal Temp I (Celsius)		
Internal Temp 2 (Celsius)		
Video Card Temp (Celsius)	70.00	
Normal Check	Danger	
(Back		
(USA) Silver Strike Bowling 2.00.01	T-Game ID 19-137504	

TROUBLESHOOTING SHORTCUTS

This section gathers many of the commonly used tests and menus into one convenient area. Check here first when troubleshooting problems or questions about the integrity of your machine.

The tests that are available in this section are:

Check Card Reader – See Hardware Tests Check Cooling – See Hardware Tests Check Hard Drive – See Hardware Tests Hardware & Software – See Hardware Tests Communications Settings – See ITNet – Not available on Arcade Collection Player Control Tests – See System Tests System Tests – See General Settings

Troubleshooting_Shortcuts
This will take you back to the previous menu.
Check Card Reader Check Cooling Check Hard Drive
Hardware & Software Communications Settings)
Player Control Tests
(USA) Silver Strike Bowling I.00.03 T-Game ID 19-000005

Descriptions of each of these tests can be found elsewhere in the manual

Back

This will take you back to the Main Menu.

SILVER STRIKE SETTINGS

Player Cost Schedule

This option allows you to adjust the amount of money it costs a player to play various game types.

Game Audits

This area allows you to view your money audits, game purchase audits, and to reset your audits.

Game Options

This area allows you to adjust options specific to Silver Strike Bowling.

Reset Leaderboards

This will clear all of the game's local leaderboards and highscore screens.

Ticket Dispenser

This area allows you to set and adjust optional ticket dispenser values and settings.

Back

This will take you back to the Main Menu.

Silver Strike Settings		
This will take you back to the Main Menu.		
to Move ← → to Change Press Start to Choose		
Player Cost Schedule		
Game Audits		
Game Options		
Reset Leaderboards		
Ticket Dispenser		
(> Back		
(USA) Silver Strike Bowling 2.00.01 T-Game ID 19-137504		

GAME OPTIONS

Game Options presents a variety of game-specific features that can be turned on or off based on the needs of your location.

Vegas Bowling

This is a selectable game mode that displays cards for every mark earned. Turn this option off in areas where the display of playing cards is not allowed.

Buy Player Cards

With this option on, players can order Player Cards from the game, which can be used for identification purposes.

Live Contest

With this option on, players can compete against other players across the country for cash and prizes during a designated period.

Note: Some states do not allow Live contests. Check your state laws before allowing this option.

Red Pin Strike

With this option on, operators can allow Red Pin Strikes. Operators can run Free Automatic Contest and Tournament Software (FACTs) using Red Pins as a criteria.

Reset Values

This will reset the fields on all game option menus to their default settings.

More

The available options are displayed on two screens. Selecting More brings you to the next page of game options.

Delay Timeout

This sets the amount of time allowed before any player input is noticed. If the timer runs out before a player moved or the ball is thrown, the ball will be lost. Use this in conjunction with the Ball Timeout setting below to determine when a game is terminated due to timeout.

Ball Timeout

This adjusts the number of balls allowed before ending an unattended game. See Delay Timeout above.

3-Frame Practice

This setting turns the 3-frame game option on or off. The default setting is Off.

Beer Frame Spotlight

This opens the Beer Frame Spotlight menu.

Reset Values

This will reset the fields on all 3 game options menus to their default settings. The Lifetime Money In field will not be affected by this function.

↑↓ to Move	← → to Change Current Value	Press Start to Choose Default Value
Delay Timeout	0:25	0.25
Ball Timeout	4 Balls	4 Bals
3-frame Practice	≡ Off	0Ħ
Be	er Frame Spotl	ight)
	Reset Values	
(USA) Silver Strike		D-Game ID 19-138257

Game Options

This will take you back to the Silver Strike Settings menu.

to Move ← → to Change Current Value	Press Start to Choose Default Value
Vegas Bowling On	On
Buy Player Cards On	On
Live Contest On	Ön
Red Pin Strike Off	Off
Reset Values	
More	
(USA) Silver Strike Bowling 3.00.04	D-Game ID 19-138257

Game Options

RESET LEADERBOARDS

Use this menu to clear the leaderboards or high-score screens. You can reset individual leaderboards or all of them at once.

	Reset Leaderboards		
This v	vill take you back to the previous menu.		
1 +	to Move 🗧 🕈 to Change Press Start to Choose		
	Reset Single Game		
	Reset Series Game		
	Reset Club 300		
	Reset Spare Challenge		
	Reset All Leaderboards		
	Back		
(USA)) Silver Strike Bowling 3.00.04 D-Game ID 19-138257		

POWERPUTT GOLF MAIN MENU

The Main Menu displays four main areas that make up System Setup mode. Please familiarize yourself with these areas, as they will help you maximize your earnings potential.

Collections & Earnings Menu – Not available in Arcade Collection

General Settings

This area allows you to adjust operator adjustables, perform system tests, and reset your game back to factory settings.

Troubleshooting Shortcuts

This section presents a variety of tests and menus that will help you troubleshoot any problems you may be having with your game. The available sections are also accessible through the other main sections.

PowerPutt GOLF Settings & Audits

This area allows you to adjust settings specific to PowerPutt GOLF including the player cost schedule, game features, and game audits.

Exit - This will exit the System Setup menus and take you back into the game's attract mode.

GENERAL SETTINGS

The General Settings menu houses various adjustable settings relating to the cabinet, and is divided into two sections.

Operator Adjustables

This area allows you to adjust options like volume, attract mode sounds, and money slot settings.

System Tests

This area allows you to perform diagnostics including video adjustments, input tests, and sound tests.

Back

This will take you back to the Main Menu.





OPERATOR ADJUSTABLES

This menu contains adjustable settings that pertain to you and your business. Please familiarize yourself with this section, as it can help you maximize the game's earning potential.

General Adjustments

This area allows you to adjust options like coin message and game mode.

Money Slot Adjustments

This area allows you to adjust the settings of your various money slots on your cabinet.

Sound Adjustments

This area allows you to adjust the various sound settings including attract mode sounds, game volume, and stereo setup.

Collection Settings

This important area allows you to adjust various fees and splits for your collections.

Reset to Factory Settings

This option allows you to reset all the settings found in the Operator Adjustables section to factory defaults.

Back

This will take you back to the General Settings menu.

GENERAL ADJUSTMENTS

Coin Message

Is set to "Insert \$" by default and requires the player to insert money. No other modes are available.

Game Mode

This lets you toggle between money/free play. The default is set to Money Play.

Reset Values

This resets all values to their default value located on this page.

Back

This will take you back to the **Operator Adjustables** menu.

to Move	+ + to Change Pro	ess Start to Choose
\subset	General Adjustments	
\subset	Money Slot Adjustmen	ts
\subset	Sound Adjustments	
\subset	Collection Settings	
	Reset to Factory Setti	ngs

Openator Adjustables

to Move	+ + to Change	Press Start to Choose
	Current Value	Default Value
Coin Message	Insert S	Treet St
Game Mode:	Money Play	Money Play

SOUND ADJUSTMENTS

In Game Volume

This option lets you adjust the In Game volume from OFF to 100%. The default is set to 30%.

Attract Volume

This option lets you adjust the Attract Volume from OFF to 100%. The default is set to 20%.

Attract Mode Sounds

This adjusts how often sounds are played in the attract mode: Never, Rarely (every 20th time), Sometimes (every 10th time), Often (every 5th time), and Always. **The default is set to On – Sometimes.**

Stereo/Mono

This option is where you select stereo or mono setup. **The default is set to Stereo.**

Reset Values

This resets all values to their default value located on this page.

Back

This will take you back to the **Operator Adjustables** menu.



	Collection Settings
This	will take you back to the Operator Adjustables menu.
t+	to Move 🗕 🖶 to Change Press Start to Choose
	Set Hardware Update Fee
	Operator/Location Income Splits
	Operator/Location Fee Splits
	Tax Settings
	Reset to Defaults
	(• Back
(US	A) PowerPutt Live LOO.00 D-Game ID 23-000098

RESET TO FACTORY SETTINGS

This menu will reset ALL settings in the Operator Adjustments section to their default values. A verification screen will display to make sure you agree to the change.

Back

This will take you back to the General Settings menu.



SYSTEM TESTS

This area allows you to perform diagnostics including video adjustments, input tests, and sound tests.

Video Tests

This area has tests that will help you to adjust your game's color, contrast, and screen size.

Sound Tests

This area has tests that will help you adjust your game's audio setup by playing a stored sound, a streaming sound, and testing the speaker(s).

Player Control Tests

This option allows you to test all inputs including trackball, buttons, money slots, etc.

Mechanical Meter Test

This test makes the hard meter adjust by one to make sure it is functioning properly.

Hardware Tests

This area includes a series of diagnostic screens and tests to help you make sure your game is functioning correctly.

Back

This will take you back to the General Settings menu.

VIDEO TESTS

The Video Tests section has a variety of tests that will help you adjust your monitor.

Color Adjustments

This area will take you to a series of tests to adjust your monitor's RGB settings to have each color display properly.

Contrast Adjustments

This area will take you to a series of tests to adjust your monitor's brightness/contrast so the game displays properly.

Screen Size Adjustment

Use this screen to align your monitor so that all the circles appear as circles and the boundary line appears on the edge of each side of the screen.

Back

This will take you back to the System Tests menu.



Arcade Collection®

 Version 1/10/23
 © Copyright Incredible Technologies, Inc. All Rights Reserved. Unauthorized duplication is a violation of applicable law. All other marks are the properties of their respective owners. All rights reserved. Commercial.

This selection	will take you back to the pr	evious menu.
to Move	← → to Change P	ress Start to Choose
\subset	Video Tests	
\subset	Sound Tests	
\subset	Player Control Tests	
\subset	Mechanical Meter	
	Hardware Tests	

COLOR ADJUSTMENTS

Color Grid Adjustment

Adjust your monitor to have each colored box display properly.

Red Screen

Adjust your monitor to have red display properly.

Green Screen

Adjust your monitor to have green display properly.

Blue Screen

Adjust your monitor to have blue display properly.

Back

This will take you back to the Video Tests menu.

CONTRAST ADJUSTMENTS

White Screen

Adjust your monitor to have white display properly.

50% White Screen

Adjust your monitor to have 50% white display properly.

25% White Screen

Adjust your monitor to have 25% white display properly.

Black Screen

Adjust your monitor to have black display properly.

Contrast Screen

This option is a test you can use to adjust your monitor's contrast and brightness settings to have the boxes displayed properly.

Note: May not work on older or often used monitors. If you have a monitor that's old or has been used often you may not be able to adjust the contrast and/or brightness levels accordingly. In this case adjust the monitor for best performance while getting close to the recommended settings.

Back

This will take you back to the Video Tests menu.

SCREEN SIZE ADJUSTMENT

Use this screen to adjust the size and aspect ratio of your picture. Press the Start button to exit.

Screen Size



This will take yo	u back to the Video Tests menu.
to Move	+ + to Change Press Start to Choose
\subset	White Screen
	50% White Screen
	25% White Screen
	Black Screen
	Contrast Screen

SOUND TESTS

Stored Sound

This will play a stored sound so you can make sure your audio setup is functioning properly.

Streaming Sound

This will play a streaming sound so you can make sure your audio setup is functioning properly.

Speaker Test

This test will say MONO if you have your game set to Mono or LEFT and RIGHT if you have it set to stereo so you can make sure your audio setup is functioning properly.

Back

This will take you back to the **System Tests** menu.

PLAYER CONTROL TESTS

Use this screen to test all of the inputs, including the trackball, buttons, and money slots. When an input is active the appropriate graphic image will light. Press the Left, Right and Start buttons simultaneously to exit this test screen.

This will take you back to the System Tests menu.				
← → to Change	Press Start to Choose			
Stored Sou	ind			
Streaming So	ound			
Speaker Te	st			
Back				
	you back to the System + + to Change Stored Sou Streaming So Speaker Te Back att live 10000			

Description			
Press Lett	+ Right + S	start to exit	
(New 25		
	Current: O		
00	-		
Max: 17		Max: 290	\sim
Current: O		Current: O	U.
	RÛIJ		
	Max: 42		
	Current: O		
Coin I	Coin 2	Serv. Test	
S		Vol. + Vol	
O Puises O Puises	O Puises		

HARDWARE TESTS

This area includes a series of diagnostic screens and tests to help you make sure your game is functioning correctly.

Hardware/Software

This area has options to view your system and USB info.

Check Hard Drive

This test checks the integrity of your hard drive's data. *Note: This test can take several minutes.*

Check Cooling

This test helps you make sure your game is functioning at the proper temperature and all fans are working.

Back

This will take you back to the **System Tests** menu.



HARDWARE/SOFTWARE

System Info

This is a list of your game's current basic system information, including Hard Drive, CPU and Video Card.

USB Info

This is a list of your game's current USB devices.

Version Info

This is a list of your game's software version.

Back

This will take you back to the Hardware Tests menu.

	H	lardware/Soft	ware
This !	selection w	ill take you back to the	previous menu.
t‡	to Move	← → to Change	Press Start to Choose
	\subset	System Info	
	\subset	USB Info	
	C	Version Info	

System Info	USB Info	Version_Info
This will take you back to the previous menu.	This will take you back to the previous menu.	This will take you back to the previous menu.
to Move ← → to Change Press Start to Choose	to Move ← → to Change Press Start to Choose	to Move + + to Change Press Start to Choose
System information	Cabinet Identification Device V6 8/29/2005	Nighthawk 05: VII.04 Game Version 2.01.06 Feb IB 2014 21.05.28 IO Brd 355 Firmware: V34 11/14/2008-000075
IGOGB ATA Hitachi HDS72IOI JPAB2IH907283R Memory/CPU	10 Card V34 II/14/2008-000098	IO Brd 355 Driver: VI6 I/07/2014 IO Brd 34IO Serial Driver: Not Used CID Brd Firmware: V6 8/29/2005
Motherboard DB65AL AAG2530-308 BOAL210005U	Cardreader Xico 7104USB-X414 21-302 v1.05 Copyright 2004	CID Brd Driver: V6 3/03/2011 Card Reader Firmware: Xico 7I04U58-X4I4 2I-302 VI05 Card Reader Driver V5 1/02/2006
Video Card ZOTAC 2NII9 GeForce GT 430/PCI/SSE2	DVD drive DVD drive not present	Game Database: VIO.0I
(USA) PowerPutt Live 20100 T-Game ID 23-000075	(USA) PowerPutt Live L00.00 D-Game ID 23-000098	(USA) PowerPutt Golf 2.01.06 OD-Game ID 23-000075

CHECK HARD DRIVE

Check File Data

This test checks the integrity of your hard drive's data.

Select **Begin Test** to initiate the process.

Note: This test can take up to 3 hours to complete.

If this test succeeds you will see the message: **Status: Hard Drive Functioning Properly.** If this test fails, you will see the message: **Hard Drive Error (#)**

Select **Back** to skip the test and return to the **Hardware Tests** menu.

Check File System

This test REBOOTS YOUR GAME and performs a low level systems check of the integrity of your hard drive.

Note: This can take several minutes.

Back

This will take you back to the Hardware Tests menu.



CHECK COOLING

This checks that your game is functioning at the proper temperature and all fans are working. The current status is color-coded for easy viewing. If the results are displayed in green, your cabinet is at normal settings.

Due to motherboard limitations, not all temperatures or fan speeds may be available.

Back

The Back button takes you back to the **Hardware Tests** menu.

TROUBLESHOOTING SHORTCUTS

This section gathers many of the commonly used tests and menus into one convenient area. Check here first when troubleshooting problems or questions about the integrity of your machine.

The tests that are available in this section are:

Check Card Reader – N/A Check Cooling Check Hard Drive Hardware & Software Communications Settings – N/A Player Control Tests System Tests Descriptions of each of these tests and sections can be found elsewhere in this manual.

Back

This will take you back to the Main Menu.

GAME OPTIONS

Game Options presents a variety of game-specific features that can be turned on or off based on the needs of your location.

Shot Timeout

This is the time allowed for each swing. If no input is noticed during this time period, the game will move on to the next turn. Default time for a stroke is one minute.

Over Par Limit

This is the maximum number of strokes over par a player can take on one hole. The default is six strokes over par.

Max Timeouts

This is the number of consecutive timeouts it takes to end a game and return to the attract mode.

Daily Contests - N/A

Poker Putt

This feature has a default setting OFF. With Poker Putt ON, the player has the ability to win playing cards for eagles, hole-in-ones and great shots.

Raw Talk

This is an optional mode that features an announcer who uses amusingly offensive language to describe some shots. This feature has a default setting OFF in case of sensitive audiences or minors who can access the game. Turn ON if these audiences are not a concern.

Banner Message – N/A

Reset Values

This will reset the fields on this screen to zero, and update the date of the last audit reset. The Lifetime Money In field will not be affected by this function.

to Move	🕈 🕈 to Change	Press Start to C	hoose
\subset	Check Cooling	\bigcirc	
\subset	Check Hard Drive		
\subset	Hardware & Softw	are	
\subset	Player Control Tes	ts	
	System Tests		

to Move	 to Change Current Value 	Press Start to Choose Default Value
Shot Timeout		HCD.
		6 Strokes
Max Timeouts		3 Timeoutz
Daily Contests	Off - N/A	off - N/A
Poker Putt	Off	QII
Raw Talk	Off	011
Operator Banner	Off + N/A	011 - N/A

All other marks are the properties of their respective owners. All rights reserved. Commercial.

RESET LEADERBOARDS

Use this menu to clear the leaderboards or high-score screens. You can reset individual course leaderboards or all of them at once.

Reset Bracket Play Leaderboard

Resets any contest leaderboard played on this machine.

Reset Skull Island/Dusty Trail/Freaky Tiki Leaderboard

More

To view the next set of Leaderboard screens: Reset Bigfoot Bend/King's Putt/ Roadside 66 and Miner 49er Leaderboards

More

To view the next set of Leaderboard screens: **Reset Haunted Hills/Camelot/Safari River and Lost Vegas Leaderboards**

Reset All Leaderboards

Resets all leaderboards on the machine.

Back

Back

This will take you back to the previous Reset Leaderboard menu.

to Me	ve	to Ch	ange	Press Start	to Choose
C	Reset E	Bracket Pl	ay Lead	erboard	>
C	Reset	Skull Islan	d Leade	rboard	\supset
C	Reset	Dusty Tra	il Leade	rboard)
C	Reset	Freaky Til	ki Leade	rboard)
		Mo			
(USA) Pov	erPutt Liv	e 100.00	D-0	Same ID 23-	860000
	Res	et Lea	derboa	ards	
(USA) Pov	Res	e 100.00	derboa	ards	00



TARGET TOSS PRO MAIN MENU

The Main Menu displays four main areas that make up System Setup mode. Please familiarize yourself with these areas, as they will help you maximize your earnings potential.

Collections & Earnings – Not available in Arcade Collection

Home Edition

General Settings

This area allows you to adjust operator adjustables, perform system tests, and reset your game back to factory settings.

Troubleshooting Shortcuts

This section presents a variety of tests and menus that will help you troubleshoot any problems you may be having with your game. The available sections are also accessible through the other main sections.

Settings & Audits

This area allows you to adjust settings specific to Target Toss

Pro: Lawn Darts and Bags including the player cost schedule, game features, and game audits.

Exit

This will exit the System Setup menus and take you back into the game's attract mode.

GENERAL SETTINGS

The General Settings menu houses various adjustable settings relating to the cabinet, and is divided into three sections.

Operator Adjustables

This area allows you to adjust options like volume, attract mode sounds, and money slot settings.

System Tests

This area allows you to perform diagnostics including video adjustments, input tests, and sound tests.

Advertisements

This area allows you to manage various graphic and text advertisements on your machine. This section is currently unavailable but is planned for a future update.

Back

This will take you back to the Main Menu.

This will ex	it you back into the game's attract mode.
to Mc	ove 🔶 🔶 to Change Press Start to Choose
(Collections & Earnings
(General Settings
(Troubleshooting Shortcuts
(Settings & Audits
	• Exit
e featur	es. and game audits.



OPERATOR ADJUSTABLES

This menu contains adjustable settings that pertain to you and your business. Please familiarize yourself with this section, as it can help you maximize the game's earning potential.

General Adjustments

This area allows you to adjust options like coin message, game mode and monitor mode.

Money Slot Adjustments

This area allows you to adjust the settings of the various money slots on your cabinet.

Sound Adjustments

This area allows you to adjust the various sound settings including attract mode sounds, game volume, and stereo setup.

Collection Settings

This important area allows you to adjust various fees and splits for your collections.

Reset To Factory Settings

This option allows you to reset all the settings found in all of the Setup Menus to factory defaults.

Exit

This will take you back to the General Settings menu.

GENERAL ADJUSTMENTS

Coin Message

This is set to "Insert \$" by default and requires the player to insert money. No other modes are available.

Game Mode

This lets you toggle between money/free play. The default setting is Money Play.

2nd Monitor Mode

You can connect a second monitor to the extra video connector on the system box, which is great for promotions or special events. Select S-Video if your second monitor is a television screen, or SVGA if your second monitor is an RGB monitor. **The default setting is S-Video.**

Note: The S-Video setting will only work if your game screen is running in high-resolution mode. If your game monitor is mid-res or low-res, the S-Video signal will not display an image.

Reset Values

This resets all values to default values located on this page.

Back

This will take you back to the **Operator Adjustables** menu.

Arcade Collection®

All other marks are the properties of their respective owners. All rights reserved. Commercial.



Gen	eral Adjust	ments
This will take you b	ack to the Operato	r Adjustables menu.
to Move	← → to Change	Press Start to Choose
	Current Value	Default Value
Coin Message:	"Insert 5"	"Insert S"
Game Mode:	Money Play	Money Play
2nd Monitor Mode	S-Video	S-Video
(USA) Bean Bags I.C	Reset Values	T-Game ID 20-138257

SOUND ADJUSTMENTS

In Game Volume

This option lets you adjust the In Game volume from OFF to 100%. The default is set to 30%.

Attract Volume

This option lets you adjust the Attract Volume from OFF to 100%. The default is set to 30%.

Attract Mode Sounds

This adjusts how often sounds are played in the attract mode: Never, Rarely (every 20th time), Sometimes (every 10th time), Often (every 5th time), and Always. **The default is set to On - Sometimes.**

Stereo/Mono

This option is where you select stereo or mono setup. **The default is set to Stereo.**

Reset Values

This resets all values to their default value located on this page.

Back

This will take you back to the Operator Adjustables menu.

RESET TO FACTORY SETTINGS

This menu will reset ALL settings in the Operator Adjustments section to their default values. A verification screen will display to make sure you agree to the change.

Back

This will take you back to the General Settings menu.

Arcade Collection[®] Version 1/10/23 © Copyright Incredible Technologies, Inc. All Rights Reserved. Unauthorized duplication is a violation of applicable law. All other marks are the properties of their respective owners. All rights reserved. Commercial.







SYSTEM TESTS

This area allows you to perform diagnostics including video adjustments, input tests, and sound tests.

Video Tests

This area has tests that will help you to adjust your game's color, contrast, and screen size.

Sound Tests

This area has tests that will help you adjust your game's audio setup by playing a stored sound, a streaming sound, and testing the speaker(s).

Player Control Tests

This option allows you to test all inputs including trackball, buttons, money slots, etc.

Mechanical Meter Test

This test makes the hard meter adjust by one to make sure it is functioning properly.

Hardware Tests

This area includes a series of diagnostic screens and tests to help you make sure your game is functioning correctly.

Back

This will take you back to the General Settings menu.

VIDEO TESTS

The Video Tests section has a variety of tests that will help you adjust your monitor.

Color Adjustments

This area will take you to a series of tests to adjust your monitor's RGB settings to have each color display properly.

Contrast Adjustments

This area will take you to a series of tests to adjust your monitor's brightness/contrast so the game displays properly.

Screen Size Adjustment

Use this screen to align your monitor so that all the circles appear as circles and the boundary line appears on the edge of each side of the screen.

Video Memory Test

Tests video memory for errors. This will reboot the machine.

Back

This will take you back to the System Tests menu.

System Tests
This selection will take you back to the previous menu.
↑↓ to Move
Video Tests
Sound Tests
Player Control Tests
Mechanical Meter
Hardware Tests
Back
(USA) TTP: LawnDarts 2.00.03 OD-Game ID 20-138257

Video Tests
This will take you back to the System Tests menu.
↑↓ to Move ← → to Change Press Start to Choose
Color Adjustments
Contrast Adjustments
Screen Size Adjustments
Video Memory Test
· Back
(USA) Bean Bags I.00.06 T-Game ID 20-138257

COLOR ADJUSTMENTS

Color Grid Adjustment

Adjust your monitor to have each colored box display properly.

Red Screen

Adjust your monitor to have red display properly.

Green Screen

Adjust your monitor to have green display properly.

Blue Screen

Adjust your monitor to have blue display properly.

Back

This will take you back to the Video Tests menu.

CONTRAST ADJUSTMENTS

White Screen

Adjust your monitor to have white display properly.

50% White Screen

Adjust your monitor to have 50% white display properly.

25% White Screen

Adjust your monitor to have 25% white display properly.

Black Screen

Adjust your monitor to have black display properly.

Contrast Screen

This option is a test you can use to adjust your monitor's contrast and brightness settings to have the boxes displayed properly.

Note: May not work on older or often used monitors. If you have a monitor that's old or has been used often you may not be able to adjust the contrast and/or brightness levels accordingly. In this case adjust the monitor for best performance while getting close to the recommended settings.

Back

This will take you back to the Video Tests menu.

SCREEN SIZE ADJUSTMENT

Use this screen to adjust the size and aspect ratio of your picture. Press the Start or Back button to exit.

HDTV SCREEN SIZE ADJUSTMENT

With HDTV screens it is possible to choose **Smaller** or **Bigger** to adjust the size of the screen. Select Done. From the **Reconfigure Screen Size** menu is the option to reboot the machine, which will start the game in the reconfigured screen size.







Arcade Collection®

ection[®] Version 1/10/23 © Copyright Incredible Technologies, Inc. All Rights Reserved. Unauthorized duplication is a violation of applicable law. All other marks are the properties of their respective owners. All rights reserved. Commercial.

SOUND TESTS

Stored Sound

This will play a stored sound so you can make sure your audio setup is functioning properly.

Streaming Sound

This will play a streaming sound so you can make sure your audio setup is functioning properly.

Speaker Test

This test will say MONO if you have your game set to Mono or LEFT and RIGHT if you have it set to stereo so you can make sure your audio setup is functioning properly.

Back

This will take you back to the System Tests menu.

PLAYER CONTROL TESTS

Use this screen to test all of the inputs, including the trackball, buttons, and money slots. When an input is active the appropriate graphic image will light. Press the Up, Down and Start buttons simultaneously to exit this test screen.





MECHANICAL METER TEST

Click Meter

This test makes the hard meter adjust by one to make sure it is functioning properly.

Back

This will take you back to the System Tests menu.

Mechanical Me	eter Test
This will take you back to the Syst	tem Tests menu.
↑↓ to Move 🔶 🔶 to Change	Press Start to Choose
Click Me	ter
(> Back	\supset
(USA) Bean Bags 1.00.06	T-Game ID 20-138257

HARDWARE TESTS

This area includes a series of diagnostic screens and tests to help you make sure your game is functioning correctly.

Hardware/Software

This area has options to view your system and USB info.

Check Hard Drive

This test checks the integrity of your hard drive's data. Note: This test can take several minutes.

Check Cooling

This test helps you make sure your game is functioning at the proper temperature and all fans are working.

Back

This will take you back to the System Tests menu.

HARDWARE/SOFTWARE

System Info

This is a list of your game's current basic system information, including Hard Drive, CPU and Video Card.

USB Info

This is a list of your game's current USB devices.

Version Info

This is your game's software version number.

Back

This will take you back to the Hardware Tests menu.

This	Hardware Tests will take you back to the System Tests menu.
tŧ	to Move 🗧 🕈 to Change Press Start to Choos
	Hardware/Software
	Check Hard Drive
	Check Cooling
(US	Bean Bags 1.00.06 T-Game ID 20-138257





	USB_Info
Th	is will take you back to the previous menu.
t	to Move 🔶 🕈 to Change 🛛 Press Start to Choose
•	Cabinet Identification Device V6 8/29/2005 - E
	IO Card V33 5/12/2006-203830
	Cardreader Xico 7104USB-X414 21-302 v1.02 Copyright 2004
•	DVD Drive DVD drive not present
	Back

CID Brd Firmware

Card Reader Drive

Game Database

CID Brd Driver Card Reader Firmware V5 8/29/2005

V4 12/22/2004

ID 20-138

V2.36

Xico 7104USB-X414 21-302 VI.02

• Back

CHECK HARD DRIVE

Check File Data

This test checks the integrity of your hard drive's data.

Select Begin Test to initiate the process.

Note: This test can take up to 3 hours to complete.

If this test succeeds you will see the message: **Status: Hard Drive Functioning Properly.** If this test fails, you will see the message: **Hard Drive Error (#)**

Select **Back** to skip the test and return to the **Check Hard Drive** menu.

Check File System

This test REBOOTS YOUR GAME and performs a low level systems check of the integrity of your hard drive.

Select Begin Test to initiate the process.

Note: This can take several minutes.

Select Back to skip the test and return to the

Back

This will take you back to the Check Hard Drive menu.

CHECK COOLING

This checks that your game is functioning at the proper temperature and all fans are working. The current status is color-coded for easy viewing. If the results are displayed in green, your cabinet is at normal settings.

Due to motherboard limitations, not all temperatures or fan speeds are available.

Back

The Back button takes you back to the **Hardware Tests** menu.



Check Coo	ling	
This checks that your game is functioning at the proper temperature and all fans are working. The Back button takes you back to the previous menu.		
↑↓ to Move ← → to Change	Press Start to Choose	
CPU Fan I (RPM)		
CPU Fan 2 (RPM)		
CPU Fan 3 (RPM)		
CPU Temp I (Celsius)		
CPU Temp 2 (Celsius)		
CPU Temp 3 (Celsius)		
Video Card Temp (Celsius)	77.00	
Normal Check	Danger	
(* Back		
(USA) Bean Bags I.00.06	T-Game ID 20-138257	

Note: Target Toss Pro: Lawn Darts and Bags are offline systems without a connection to ITNet. Therefore, troubleshooting data, audits and operator adjustable items are NOT available online through your secure ITNet - Remove account.

TROUBLESHOOTING SHORTCUTS

This section gathers many of the commonly used tests and menus into one convenient area. Check here first when troubleshooting problems or questions about the integrity of your machine.

The tests that are available in this section are:

- Check Cooling
- Check Hard Drive
- Hardware & Software
- Player Control Tests
- System Tests

Descriptions for each of these tests and sections can be found elsewhere in this manual.

Back

This will take you back to the Main Menu.

GAME OPTIONS

Game Options

This selection will take you back to the previous menu.

🛏 🔿 to Change

Current Value

to Move

(USA) TTP: LawnDarts 2.00.03

The Game Options menu presents a variety of game-specific features that can be turned on or off based on the needs of your location.

Delay Timeout

This is the time allowed for each throw. If no input is noticed during this time period, the game will move on to the next turn. Default time for a throw is 25 seconds.

Throw Timeout

This is the number of consecutive timeouts it takes to end a game and return to attract mode.

Vegas/Poker Games

This is a selectable game mode that displays cards for every bag in the hole. Turn this option off in areas where the display of playing cards is not allowed. Also turns poker darts game on/off.

Vegas/Poker On On Practice Throws Off Off Raw Talk On Off Poker Tournament Off Off Reset Values Back

Practice Throws

A one-player game allows for 1, 2, 3 or 4 practice throws before scoring begins. This is a nice way to introduce new players to the feel and play of the game. Turn this feature to off if no practice bags are desired.

Raw Talk

This is an optional mode that features an announcer who uses amusingly offensive language to describe some shots.

Reset Values

This will reset the fields on this screen to the default settings.

Poker Tournament

Options for 4-player, 8-player and 16-player tournaments. In these tournaments, players face off against one another in single-elimination match play; winners of each game move on until one player is the champion.

Arcade Collection®

Version 1/10/23

© Copyright Incredible Technologies, Inc. All Rights Reserved. Unauthorized duplication is a violation of applicable law. All other marks are the properties of their respective owners. All rights reserved. Commercial.

Press Start to Choose

OD-Game ID 20-138257

Default Value

RESET LEADERBOARDS

Selecting **Reset Leaderboards** allows you to reset the leaderboards for both games. The Lawn Darts and Bags leaderboard information is specific to those games.



LEADERBOARDS - TTP: BAGS

Use this menu to clear the leaderboards or high-score screens. You can reset individual leaderboards or all of them at once. To prevent unintended deletions, a confirmation screen asks if you are sure you want to reset the leaderboard.

Inning Leaderboards

The highest score in one inning.

Top Baggers

The best complete game scores.

Team Leaderboard

Best two-player team scores

Reset All of the Above Leaderboards

Use this to clear all bags leaderboards at one time.

LEADERBOARDS – TTP: LAWN DARTS

The menu on the Lawn Darts screen allows reset for one or all of the Lawn Darts games.



Reset Leaderboards
This selection will take you back to the previous menu.
★↓ to Move ← → to Change Press Start to Choose
Reset Classic Lawn Darts
Reset 501
Reset Cricket
Reset Poker
Reset all of the above
Back
(USA) TTP: LawnDarts 2.00.03 OD-Game ID 20-138257